

EN Specifications

Amplifier	
Maximum output power	500 W *
Audio Inputs	
Input A / B	XLR, servo-balanced
Sensitivity	+4 dBu @ 0 dB (center position) for full rated power
Input impedance	12 k Ω unbalanced, 24 k Ω balanced
Audio Outputs	
Thru A / B	XLR, servo-balanced
Output A / B	XLR, servo-balanced
Output impedance	300 Ω unbalanced, 600 Ω balanced
High-pass filter	100 Hz, Butterworth, 18 dB slope
Controls	
Level	$-\infty$ to +6 dB
Boost frequency	40 Hz - 90 Hz; +10 dB
Boost	Switchable
High cut	70 - 150 Hz, Butterworth, 24 dB slope
Phase	Switchable
System Data	
Frequency range	45 Hz - 180 Hz (-10 dB)
Frequency response	60 Hz - 130 Hz (+/-3 dB)
Signal-to-noise (20 Hz to 20 KHz)	>100 dB
Sound pressure level (half space)	max. 122 dB @ 1 m
Woofer	307 mm / 12" 8 Ω
Limiter	Optical
Indicators	
Signal LED	Green
Limit LED	Red
Power LED	Amber
Circuit Protection	
Amplifier protection	Full short circuit, open circuit, thermal protection
Load Protection	Turn-on/off muting
Power Supply, Voltage (Fuses)	
USA / Canada	120 V~, 60 Hz (T 6.3 A H 250 V)
UK / Australia / Europe	220-240 V~, 50/60 Hz (T 3.15 A H 250 V)
Korea / China	220-240 V~, 50/60 Hz (T 3.15 A H 250 V)
Japan	100 V~, 50/60 Hz (T 6.3 A H 250 V)
Power consumption	110 W
Mains connection	Standard IEC receptacle
Dimensions / Weight	
Dimensions (H x W x D)	432 x 375 x 423 mm (17.0 x 14.8 x 16.7")
Weight	19.5 kg (43.1 lbs)

Other important

EN Important information

- 1. Register online.** Please register your new Music Tribe equipment right after you purchase it by visiting musictribe.com. Registering your purchase using our simple online form helps us to process your repair claims more quickly and efficiently. Also, read the terms and conditions of our warranty, if applicable.
- 2. Malfunction.** Should your Music Tribe Authorized Reseller not be located in your vicinity, you may contact the Music Tribe Authorized Fulfiller for your country listed under "Support" at musictribe.com. Should your country not be listed, please check if your problem can be dealt with by our "Online Support" which may also be found under "Support" at musictribe.com. Alternatively, please submit an online warranty claim at musictribe.com BEFORE returning the product.
- 3. Power Connections.** Before plugging the unit into a power socket, please make sure you are using the correct mains voltage for your particular model. Faulty fuses must be replaced with fuses of the same type and rating without exception.

ES Aspectos importantes

- 1. Registro online.** Le recomendamos que registre su nuevo aparato Music Tribe justo después de su compra accediendo a la página web musictribe.com. El registro de su compra a través de nuestro sencillo sistema online nos ayudará a resolver cualquier incidencia que se presente a la mayor brevedad posible. Además, aproveche para leer los términos y condiciones de nuestra garantía, si es aplicable en su caso.
- 2. Averías.** En el caso de que no exista un distribuidor Music Tribe en las inmediaciones, puede ponerse en contacto con el distribuidor Music Tribe de su país, que encontrará dentro del abastecido "Support" de nuestra