

EN Specifications

EN Important information

System Data	VP2520	VP1800S	VP1520	VP1220F	VP1220
Peak Power	2000 W	1600 W	1000 W	800 W	800 W
Type	2 1/2-way full-range loudspeaker	Subwoofer	2-way full-range loudspeaker	2-way full-range loudspeaker	2-way full-range loudspeaker
Frequency Response	40 Hz – 20 kHz	35 Hz – 250 Hz	45 Hz – 20 kHz	55 Hz – 20 kHz	50 Hz – 20 kHz
Impedance	4 Ohms	8 Ohms	8 Ohms	8 Ohms	8 Ohms
Sound Pressure Level (SPL)	96 dB (Full space, 1 W @ 1 m)	100 dB (Half space, 1 W @ 1 m)	94 dB (Full space, 1 W @ 1 m)	93 dB (Full space, 1 W @ 1 m)	93 dB (Full space, 1 W @ 1 m)
Dispersion	70° x 50°	n/a	70° x 50°	70° x 50°	70° x 50°
Crossover Frequency	2.2 kHz	LP 150 Hz	2.5 kHz	2.5 kHz	2.5 kHz
Rigging Fittings	ergonomically shaped handle	ergonomically shaped handle; 35 mm pole socket	ergonomically shaped handle; integral tripod/stand adapter	ergonomically shaped handle	ergonomically shaped handle; integral tripod/stand adapter
Components					
HF Driver	1.75" titanium-diaphragm compression driver	—	1.75" titanium-diaphragm compression driver	1.75" titanium-diaphragm compression driver	1.75" titanium-diaphragm compression driver
LF Driver	2 x 15" / 385 mm	18" / 460 mm	15" / 385 mm	12" / 307 mm	12" / 307 mm
Dimensions/Weight					
Width	18.7" / 475 mm	20.9" / 530 mm	17.9" / 455 mm	7.3" / 440 mm	14.6" / 370 mm
Height	41.9" / 1065 mm	25.6" / 650 mm	27.0" / 685 mm	16.9" / 430 mm	23.6" / 600 mm
Depth	20.1" / 510 mm	24.2" / 615 mm	18.3" / 465 mm	22.6" / 575 mm	16.9" / 430 mm
Weight	87.7 lbs / 39.8 kg	91.3 lbs / 41.4 kg	49.8 lbs / 22.6 kg	35.7 lbs / 16.2 kg	39.5 lbs / 17.9 kg

Other important

- 1. Register online.** Please register your new Music Tribe equipment right after you purchase it by visiting musictribe.com. Registering your purchase using our simple online form helps us to process your repair claims more quickly and efficiently. Also, read the terms and conditions of our warranty, if applicable.
- 2. Malfunction.** Should your Music Tribe Authorized Reseller not be located in your vicinity, you may contact the Music Tribe Authorized Fulfiller for your country listed under "Support" at musictribe.com. Should your country not be listed, please check if your problem can be dealt with by our "Online Support" which may also be found under "Support" at musictribe.com. Alternatively, please submit an online warranty claim at musictribe.com BEFORE returning the product.
- 3. Power Connections.** Before plugging the unit into a power socket, please make sure you are using the correct mains voltage for your particular model. Faulty fuses must be replaced with fuses of the same type and rating without exception.

ES Aspectos importantes

- 1. Registro online.** Le recomendamos que registre su nuevo aparato Music Tribe justo después de su compra accediendo a la página web musictribe.com. El registro de su compra a través de nuestro sencillo sistema online nos ayudará a resolver cualquier incidencia que se presente a la mayor brevedad posible. Además, aproveche para leer los términos y condiciones de nuestra garantía, si es aplicable en su caso.
- 2. Averías.** En el caso de que no exista un distribuidor Music Tribe en las inmediaciones, puede ponerse en contacto con el distribuidor Music Tribe de su país, que encontrará dentro del abastecido "Support" de nuestra